UNIVERSITY^{OF} BIRMINGHAM University of Birmingham Research at Birmingham

Soret lens-antenna based on the fishnet metamaterial

Orazbayev, B.; Beruete, M.; Crespo, Gonzalo; Teniente, J.; Navarro-Cia, Miguel

DOI: 10.1109/EuCAP.2016.7481900

Document Version Peer reviewed version

Citation for published version (Harvard):

Orazbayev, B, Beruete, M, Crespo, G, Teniente, J & Navarro-Cia, M 2016, Soret lens-antenna based on the fishnet metamaterial. in 2016 10th European Conference on Antennas and Propagation (EuCAP). Institute of Electrical and Electronics Engineers (IEEE). https://doi.org/10.1109/EuCAP.2016.7481900

Link to publication on Research at Birmingham portal

General rights

Unless a licence is specified above, all rights (including copyright and moral rights) in this document are retained by the authors and/or the copyright holders. The express permission of the copyright holder must be obtained for any use of this material other than for purposes permitted by law.

•Users may freely distribute the URL that is used to identify this publication.

•Users may download and/or print one copy of the publication from the University of Birmingham research portal for the purpose of private study or non-commercial research.

•User may use extracts from the document in line with the concept of 'fair dealing' under the Copyright, Designs and Patents Act 1988 (?) •Users may not further distribute the material nor use it for the purposes of commercial gain.

Where a licence is displayed above, please note the terms and conditions of the licence govern your use of this document.

When citing, please reference the published version.

Take down policy

While the University of Birmingham exercises care and attention in making items available there are rare occasions when an item has been uploaded in error or has been deemed to be commercially or otherwise sensitive.

If you believe that this is the case for this document, please contact UBIRA@lists.bham.ac.uk providing details and we will remove access to the work immediately and investigate.

Soret Lens-Antenna based on the Fishnet Metamaterial

B. Orazbayev¹, M. Beruete^{1,2}, V. Pacheco-Peña¹, G. Crespo¹, J. Teniente¹, M. Navarro-Cía³

¹ Antennas Group-TERALAB, Public University of Navarra, 31006 Pamplona, Spain. miguel.beruete@unavarra.es

² Institute of Smart Cities, Public University of Navarra, 31006 Pamplona, Spain

³ Optical and Semiconductor Devices Group, Department of Electrical and Electronic Engineering, Imperial College London, London SW7 2BT, UK. m.navarro-cia@bham.ac.uk

Abstract— In this work we present the design, numerical and experimental results for an ultrathin Soret fishnet metamaterial lens working at $f_{exp} = 96.45$ GHz. The fishnet metamaterial with effective refractive index close to zero (n = -0.06) is introduced on the back side of the classical Soret lens in order to improve its efficiency. The experimental results are in good agreement with simulation results and demonstrate half-wavelength focal length and spot size. In a lens antenna configuration a high gain of 10.64 dB was measured at the operation frequency. The presented lens has a low-cost compact design, and may find applications in integrated lens antenna systems.

Index Terms—antenna, metamaterial, propagation, Fresnel zone.

I. INTRODUCTION

A Soret lens, like any member of Fresnel zone plate lenses, consists of alternating concentric opaque and transparent zones [1]. Opaque zones block the part of the incident wave that otherwise would interfere destructively at the focal point. Unfortunately, the efficiency of this lens is low because half of the power is blocked [2], [3]. A possible solution to increase the efficiency is to replace opaque areas by dielectric, which provides an additional phase shift of π to the transmitted wave. In such design a constructive interference between all zones occurs at the focal point. However, such technique increases the thickness of lenses and complicates the manufacturing process [2]–[4].

A smarter solution could be to use metamaterials [5] in the lens design, replacing the conventional dielectrics. Given the possibility of manipulating the values of permittivity and permeability independently, metamaterials provide more possibilities for control of electromagnetic waves [6]. One of the most promising metamaterials for the millimeter range is the fishnet structure (stacked subwavelength hole arrays), which has low losses in this range [7], [8]. The fishnet metamaterial has been successfully used to design lenses for the millimeter range [9]-[12]. Surface currents, excited on the surface of the plates of the fishnet improve the adaptation of the lens and its illumination efficiency [13], [14]. Moreover, designing the fishnet metamaterial to behave as a medium with index of refraction close to zero provides a quasi-plane-wave front on its surface [15], [16], improving the gain and sidelobe levels of an Soret metalens antenna.

In this work a Soret lens based on a fishnet metamaterial is designed, fabricated and measured [17]. The experimental focus is placed at 1.973 mm ($0.6\lambda_0$) in good agreement with the numerical results. The metalens-antenna shows an experimental gain of 10.64 dB at the frequency $f_{exp} = 96.45$ GHz.

II. LENS DESIGN

A. Fishnet metamaterial

The unit cell of a fishnet metamaterial implemented in the Soret lens consists of a metal plate (aluminum of thickness 0.017 mm) embedded between two dielectric plates (Rogers RO5880TM with thickness 0.19 mm) of permittivity $\varepsilon_r = 2.2$ and loss tangent tan $\delta = 9 \times 10^{-4}$. Therefore, the dimensions of the unit cell are: $d_x = 1.26$ mm, $d_y = 2.1$ mm, $d_z = 0.398$ mm, hole diameter $a = d_y/4 = 0.525$ mm; see Fig. 1(a). For these parameters, the cut-off frequency of the hole fundamental TE₁₁ mode is 112 GHz. The effective refractive index is evaluated from the dispersion diagram computed with the eigen-mode solver of CST Microwave StudioTM. At the design frequency f = 95 GHz, the fishnet metamaterial behaves as a medium with n = -0.06.



Fig.1. (a) Fishnet metamaterial unit cell. (b) Photograph of the fabricated metalens (without first protective layer)

B. Fresnel zones

Fresnel zone plate lens consists of circular zones whose radii are calculated by the following equation [2], [3]:

$$r_i = \sqrt{\frac{2FL \cdot \lambda_0 \cdot i}{p} + \left(\frac{i \cdot \lambda_0}{p}\right)^2} \tag{1}$$

where λ_0 is the wavelength at the working frequency, *FL* is the focal length, *i* is the number of Fresnel zones and *p* is the number of phase quantization levels. In the designed lens *i* = 7 is used, with outer radius $r_7 = 12.5$ mm. The other parameters are: *FL* = 1.58 mm (0.5 λ_0), *p* = 2. The fabricated prototype with these design parameters is shown in Fig. 1(b). The overall dimensions are 32 mm × 32 mm × 1.973 mm.

III. RESULTS

First, the designed lens was numerically analyzed using the transient solver of CST Microwave Studio™. In order to reduce the computation time, and considering the symmetry of the problem, magnetic and electrical symmetries were imposed on the yz- and xz-planes, respectively; see coordinate axis in Fig. 1. A vertically polarized wave (E_v) was used to illuminate the lens from its flat side. In Fig. 2 (a, b) you can see numerical results for the field distribution in (a) the xz-plane and (b) the *yz*-plane at slightly different from the design frequency $f_{sim} =$ 98 GHz, where the maximum power at the focal spot is detected. This shift can be explained by an additional protective layer in the final prototype which was not taken into account in the design. The characteristics of the focus in each of the planes are: focal length $FL = 1.94 \text{ mm} (0.64\lambda_0)$, depth of focus $DF = 1.97 \text{ mm} (0.65\lambda_0)$, and $FWHM_1 = 1.39 \text{ mm}$ $(0.46\lambda_0)$ and $FWHM_2 = 1.58 \text{ mm} (0.52\lambda_0)$ for xz- and yz-planes, respectively.



Fig.2. Normalized field distribution in *xz*-plane (a,c) and *yz*-plane (b,d) for numerical (top) and experimental (below) results.

Next, the lens was experimentally analyzed using the vector network analyzer ABmm VNA [18]. The distribution of the experimental electric field amplitude at frequency $f_{exp} = 96.45$ GHz (where the maximum focus was detected) can be seen in Fig. 2 (c, d), where (c) shows the *xz*-plane and (d) the *yz*-plane. The parameters of focus are: focal length *FL* = 1.9 mm (0.64 λ_0), depth of focus *DF* = 2 mm (0.64 λ_0) and *FWHM*₁ = 1.44 mm (0.46 λ_0) and *FWHM*₂ = 1.73 mm (0.56 λ_0) for *xz*-and *yz*-plane respectively. It is obvious that the numerical and experimental results are in good agreement.

Finally, the performance of the lens at the working frequency was analyzed, for the case when the lens is used to improve the radiation pattern of a low directional antenna. To this end, at the focal point of the metalens a waveguide probe (an open rectangular waveguide with chamfered edges to avoid reflections) was placed, acting as a transmitter. The radiation pattern of metalens-antenna system was captured by a high gain horn antenna. The numerical and experimental radiation patterns are shown in Fig. 3 (a, b) for *E*- (a) and *H*-plane (b) respectively. The disagreement between simulation and experiment for the *E*-plane is noticeable and can be explained by several factors. First, the errors in the measurements, such as displacement of the waveguide probe, can significantly widen the beam. Moreover, since the numerical and experimental focal maxima appear at different frequencies therefore the experimental and simulation radiation patterns are also obtained for different frequencies f_{sim} and f_{exp} , which results in the wider beamwidth [17].

High gain of 10.64 dB was measured at frequency f_{exp} = 96.45 GHz while the gain predicted by the simulation was 14.6 dB. The disagreement may be explained by dielectric losses and air gap between the dielectric plates.



Fig. 3. Normalized radiation pattern for *E*-plane (a) and *H*-plane (b), measured with waveguide probe.

Additional measurements were performed for the radiation patterns in order to confirm the performance of the metalensantenna. To this end the waveguide probe at the focal position was replaced by a high gain horn antenna. Due to the changes in the setup the focal position with maximum power has shifted slightly from $FL_{probe} = 1.9 \text{ mm} (0.64\lambda_0)$ to $FL_{horn} = 2.3 \text{ mm} (0.64\lambda_0)$ with the frequency $f_{horn} = 98.6 \text{ GHz}$, which is closer to the f_{sim} . The normalized numerical and experimental radiation patterns for this setup are shown in Fig. 4(a,b) for *E*-(a) and *H*-plane (b) respectively. The results (measurement vs. simulation) are in better agreement than for the case when the waveguide probe is used. We believe that this is because the configuration is significantly more robust to misalignment and we are investigating this issue under this assumption.

Analogously to the case with the waveguide probe, the high gain of 18.2 dB was measured at frequency $f_{horn} = 98.6$ GHz. The higher gain can be explained by closer frequencies and the higher illumination efficiency when the horn antenna is used as source.



Fig. 4. Normalized radiation pattern for *E*-plane (a) and *H*-plane (b), measured with horn antenna.

IV. CONCLUSIONS

In conclusion, the Soret lens based on a fishnet metamaterial and working in millimeter waves has been designed, fabricated and measured. A good agreement between the simulation and experimental results has been shown. The proposed design, which is low-profile, relatively inexpensive and easy to manufacture, demonstrates a solution to improve the radiation characteristics of a Soret fishnet metalensantenna. Such compact devices may find applications in wireless or radar systems.

ACKNOWLEDGMENT

This work is sponsored by Spanish Government under contracts TEC2014-51902-C2-2-R. B. O. is sponsored by Spanish Ministerio de Economía y Competitividad under grant FPI BES-2012-054909. M. B. is sponsored by the Spanish Government via RYC-2011-08221. V.P.-P. is sponsored by Spanish Ministerio de Educación, Cultura y Deporte under grant FPU AP-2012-3796. M. N.-C. is supported by the Imperial College Junior Research Fellowship.

REFERENCES

- J. L. Soret, "Ueber die durch Kreisgitter erzeugten Diffractionsphänomene," Ann. der Phys. und Chemie, vol. 232, no. 9, pp. 99–113, 1875.
- H. D. Hristov, Fresnel Zones in Wireless Links, Zone Plate Lenses and Antennas. Artech House, Norwood, MA, 2000.
- [3] I. V Minin and O. Minin, Diffractional Optics of Millimetre Waves. CRC Press, Bristol, 2004.
- [4] H. Hristov and M. Herben, "Millimeter-wave Fresnel-zone plate lens and antenna," *IEEE Trans. Microw. Theory Tech.*, vol. 43, no. 12, pp. 2779–2785, 1995.
- [5] R. Marqués, F. Martín, and M. Sorolla, *Metamaterials with negative parameter : theory, design, and microwave applications*. John Wiley & Sons, 2008.
- [6] A. Demetriadou and Y. Hao, "Slim Luneburg lens for antenna applications.," Opt. Express, vol. 19, no. 21, pp. 19925–34, Oct. 2011.
- [7] M. Beruete, M. Sorolla Ayza, and I. Campillo, "Left-handed extraordinary optical transmission through a photonic crystal of subwavelength hole arrays," *Opt. Express*, vol. 14, no. 12, p. 5445, 2006.
- [8] M. Navarro-Cia, M. Beruete, M. Sorolla, I. Campillo, M. Sorolla Ayza, and I. Campillo, "Negative refraction in a prism made of stacked subwavelength hole arrays.," *Opt. Express*, vol. 16, no. 2, pp. 560–566, Jan. 2008.
- [9] M. Beruete, M. Navarro-Cía, M. Sorolla Ayza, and I. Campillo, "Planoconcave lens by negative refraction of stacked subwavelength hole arrays," *Opt. Express*, vol. 16, no. 13, pp. 9677–9683, Jun. 2008.
- [10] M. Navarro-Cía, M. Beruete, I. Campillo, and M. Sorolla Ayza, "Beamforming by Left-Handed Extraordinary Transmission Metamaterial Bi- and Plano-Concave Lens at Millimeter-Waves," *IEEE Trans. Antennas Propag.*, vol. 59, no. 6, pp. 2141–2151, Jun. 2011.
- [11] V. Pacheco-Peña, B. Orazbayev, V. Torres, M. Beruete, and M. Navarro-Cía, "Ultra-compact planoconcave zoned metallic lens based on the fishnet metamaterial," *Appl. Phys. Lett.*, vol. 103, pp. 183507–1–12, 2013.
- [12] B. Orazbayev, V. Pacheco-Peña, M. Beruete, and M. Navarro-Cía, "Exploiting the dispersion of the double-negative-index fishnet metamaterial to create a broadband low-profile metallic lens," *Opt. Express*, vol. 23, no. 7, p. 8555, Mar. 2015.
- [13] T. Matsui, A. Agrawal, A. Nahata, and Z. V. Vardeny, "Transmission resonances through aperiodic arrays of subwavelength apertures.," *Nature*, vol. 446, no. 7135, pp. 517–21, Mar. 2007.
- [14] M. Beruete, M. Navarro-Cía, F. Falcone, M. Sorolla, I. Campillo, J. E. Rodriguez-Seco, E. Perea, and I. J. Nunez-Manrique, "Extraordinary Transmission surfaces as superstrate," in 2009 Mediterrannean Microwave Symposium (MMS), 2009, pp. 1–4.
- [15] A. Alù, M. M. Silveirinha, A. Salandrino, and N. Engheta, "Epsilon-near-zero metamaterials and electromagnetic sources: Tailoring the radiation phase pattern," *Phys. Rev. B*, vol. 75, no. 15, p. 155410, Apr. 2007.
- [16] M. Navarro-Cía, M. Beruete, I. Campillo, and M. Sorolla, "Enhanced lens by ε and μ near-zero metamaterial boosted by extraordinary optical transmission," *Phys. Rev. B - Condens. Matter Mater. Phys.*, vol. 83, no. 11, pp. 115112–1–5, Mar. 2011.
- [17] B. Orazbayev, M. Beruete, V. Pacheco-Peña, G. Crespo, J. Teniente, and M. Navarro-Cía, "Soret fishnet metalens antenna.," *Sci. Rep.*, vol. 4, p. 9988, Jan. 2015.
- [18] CST Computer Simulation Technology AG, "CST Microwave Studio." http://www.cst.com, 2015.